

Change IP Details Permanent

Feb 2017

Introduction

To permanently change the IP details you must first be able to connect to the VSPP (see Change IP Address CMD Line). Once connected we need to edit the VSPP Configuration.

The VSPP is configured using a powerful tool called SYSU. SYSU created a file called system.ini that contains all of our configuration parameters.

Using SYSU

To change the VSPP configuration run the following:

```
sysu edit
```

This will load the system.ini into Vi.

```
<sxh [xml]; options for SyntaxHighlighter> ##### system Topology ##### ## all parameters marked with green should be changed
with relevant site configuration ## ##### Region and Rack properties ##### [aio-region] type = region inherit = MANAGER:REGION
pods = aio-pod [aio-pod] type = pod inherit = MANAGER:POD raid.mode = 0 segment.size = 1 geo.ids = 1 subnets = 0.0.0.0/0 # Do not
change volume.line.size volume.line.size = 96 [pod-group-aio] type = pod_group inherit = MANAGER:POD_GROUP pods = aio-pod [AIO] type
= stateful default_gateway = MNG os = CENTOS6.6.P30.3-X86_64 machine = SERVER site = FX-SITE node.aio1 = aio103, MNG-20,
VIDEO-20.1 repos = file:/var/sysu/repos/centos6.6, file:/var/sysu/repos/fabrix_sw apps = syspu, dns, manager, postgres, gui, storage,
streamer, graphite, riemann, mon_agent nic = MNG|ETH2, VIDEO|ETH3 pod = aio-pod [FX-SITE] type = site syspu = syspu ntp.servers =
192.168.100.150 domains = system.fx timezone = Europe/London # Fabrix brand and version Type :quit<Enter> to exit Vim # Fabrix brand
and version brand = fabrix version = 3.8 [syspu] type = application inherit = SYSPU:APP # Changing HTTPD port that is used by Syspu (the
default is port 80) # port = 82 [mon_agent] type = application inherit = MON_AGENT:APP # push.manager is relevant for Manager >= 3.5
push.manager = manager push.riemann = riemann # A graphite prefix that will be use by mon_agent parser.ini.mon_agent.ini.107 =
general@prefix_name = Ericsson.VSPP [graphite] type = application inherit = GRAPHITE:APP [riemann] type = application inherit =
RIEMANN:APP [dns] type = application inherit = DNS:APP domains = system.fx # DNS additional nameservers (optional) nameservers =
192.168.100.150 [manager] type = application inherit = MANAGER:APP # Cluster: list of define application sections, these applications will
be cluster under this manager. cluster = storage, streamer # Gui application section gui.section = gui # PostgreSQL application section
db.section = postgres fxdb.domains = manager.system.fx fxdb.domains = manager.system.fx enable.api = True regions = aio-region #
Manager application configuration parser.ini.manager.ini.100 = general@DISABLE_SSL = 1 parser.ini.manager.ini.101 =
general@SRM_SERVER_ADDR = parser.ini.manager.ini.102 = general@PUBLIC_LISTENING_ADDR=9090 parser.ini.manager.ini.103 =
general@USE_SYSLOG = 0 parser.ini.manager.ini.104= general@USE_STREAMER_REPORT_FOR_LINK_STATUS = false [postgres] type =
application inherit = POSTGRES9:APP # Solid DB core limitation (for more details see Appendix E): # RSDVR private copy - Managers should
use all cores in the machine (remove this configuration parameter) # All other production systems - Manager Solid should be limited to four
cores: 0-3 # Lab systems - Manager Solid should be limited to one core: 0 # database.cores = 0 # Network layout # db network defines the
interface for client connection (all client will be configure according) db.network = management # Solid application parameters # Solid
dedicated disk for transaction logs (Uncomment in case you set up a dedicated disk) # parser.ini.solid.ini.100 = Logging@LogDir =
/data/solid_logs [gui] type = application inherit = GUI:APP db.section = postgres # Enabling GUI dashboard by referencing to graphite
section: graphite.section = graphite parser.property.configuration.properties.100 = show.all = true [storage] type = application inherit =
STORAGE_SERVICE_LEDS_SUPPORT:APP # Network layout # Cluster is the application interconnect (disks) communication network
cluster.network = management # storage application configuration parser.ini.storage-server.ini.100 = general@USE_SYSLOG = 0
parser.ini.storage-server.ini.101 = general@WORKING_PATH = /opt/Fabrix.TV/vs-storage/Disk parser.ini.storage-server.ini.102 =
general@LOG_FILENAME = /opt/Fabrix.TV/logs/storage.log parser.ini.storage-server.ini.103 = general@DISABLE_SSL = 1 # These
parameters are controlling the application memory allocation, for small server (VM) use "50" # SERVER_DATA_CACHE_SIZE is memory per
disk in MB parser.ini.storage-server.ini.104 = general@SERVER_DATA_CACHE_SIZE = 50 parser.ini.storage-server.ini.105 =
general@CLIENT_DATA_CACHE_SIZE = 50 # Disable LED features (Normally in VM environment) parser.ini.storage-server.ini.106 =
general@USING_VIRTUAL_BLOCK_DEVICE = false parser.ini.storage-server.ini.107 = general@IGNORE_BLOCK_DEVICES = sda
parser.ini.storage-server.ini.108 = general@DEVICE_FILE_NAME_PREFIX = sd parser.ini.storage-server.ini.109 = USING_PHYSICAL_DISK =
true parser.ini.storage-server.ini.110 = LED_ENABLED = false [streamer] type = application inherit = STREAMER:APP # BW Properties
max.cdn = 1G max.streaming = 1G max.ingest = 1G max.total = 1G abr_streaming = true # Network layout # External is for "video
stream" (playout) network external.network = management # Ingest is the "video ingest" network ingest.network = video # Cluster is the
application interconnect (disks) communication network cluster.network = management # Uncomment and update Streamer virtual
network # virtual.network = management # streamer INI parameters parser.ini.streamer.ini.100 = general@STREAMER_ADDR = 2929
```

Last update: 2023/03/09 22:35 change_ip_details_permanent http://cameraangle.co.uk/doku.php?id=change_ip_details_permanent&rev=1488288222

```
parser.ini.streamer.ini.101 = general@LOG_FILENAME = /opt/Fabrix.TV/logs/streamer.log parser.ini.streamer.ini.102 =
general@STRING_TABLES_FILE = /opt/Fabrix.TV/Configuration_Files/String_Tables.xml # These parameters are controlling the application
memory allocation, for small server (VM) use "50" parser.ini.streamer.ini.103 = general@TOTAL_STREAMING_THROUGHPUT = 450
parser.ini.streamer.ini.104 = general@CLIENT_DATA_CACHE_SIZE = 200 parser.ini.streamer.ini.105 =
general@TOTAL_STREAMING_THROUGHPUT = 450 parser.ini.streamer.ini.106 = general@DISABLE_SSL = 1 parser.ini.streamer.ini.107 =
general@USE_SYSLOG = 0 ##### Network properties ##### [MNG] type = network name = management network = 192.168.27.0 netmask
= 255.255.255.0 next_hop = 192.168.27.254 [VIDEO] type = network name = video network = 10.10.0.0 netmask = 255.255.0.0 next_hop
= 10.10.255.254 ##### Nic Properties ##### [ETH0] type = nic device = eth0 bootproto = static [ETH1] type = nic device = eth1
bootproto = static [ETH2] type = nic device = eth2 bootproto = static [ETH3] type = nic device = eth3 bootproto = static ##### Machine
Property ##### [SERVER] type = machine # IBM-COMMON (for all IBM servers), HP-COMMON (for all HP servers) for other brands inherit
SERVER-COMMON inherit = SERVER-COMMON # uncomment, below "kcmdline" empty attribute incase of virtual environment! # kcmdline
= # Number of disks used by VSPP Storage: storage.disks = 4 </sxh>
```

From:
<http://cameraangle.co.uk/> - WalkerWiki - wiki.alanwalker.uk

Permanent link:
http://cameraangle.co.uk/doku.php?id=change_ip_details_permanent&rev=1488288222

Last update: 2023/03/09 22:35

