

# Encoding Live entries in Controller missing IP and Details

Oct 2018

For reference, this behaviour was observed when using the following Encoding Live and Controller versions:

EL  
Controller

After installing Controller on it's own server, MFEL is then installed on a separate server, without any other software. When running the following command:

```
/opt/ericsson/encoding-live-server/setup/configure.sh --localIP x.x.x.x --serverID xx --controllerIP x.x.x.x
```

The entry is added to the Controller, but some information is missing.

MediaKind

MediaKind Controller

000admin

Home

Services

Servers

Alarms

Templates

Failover

Settings

Home / Servers

Search in table

Name	IP Address	Processing Type	Software	Status	Actions
MFEL1	N/A	Live Encoding	N/A	connected	
MFEL2	N/A	Live Encoding	N/A	N/A	
MFEL3	N/A	Live Encoding	N/A	N/A	
MFEL4	N/A	Live Encoding	N/A	N/A	
MFEL5	N/A	Live Encoding	N/A	N/A	
ctrlr1	192.168.81.11	Controller, Licensing	ericsson-controller 10.1.10.58 , ericsson-license-manager 0.2.9-0	connected	

Rows per page: 20

To fix this, use the following instructions:

```
On the controller machine, download the file /etc/ericsson/secrets/mongo/secrets.ini

On each Encoding Live Server, create this folder: /etc/ericsson/secrets/mongo/

Command: mkdir -p /etc/ericsson/secrets/mongo/

Copy the file secrets.ini downloaded from the Controller to this path /etc/ericsson/secrets/mongo/

Relaunch /opt/ericsson/encoding-live-server/setup/configure.sh --localIP x.x.x.x --serverID xx
--controllerIP x.x.x.x
```

From:

<http://cameraangle.co.uk/> - WalkerWiki - wiki.alanwalker.uk

Permanent link:

[http://cameraangle.co.uk/doku.php?id=encoding\\_live\\_entries\\_in\\_controller\\_missing\\_ip\\_and\\_details&rev=1538721954](http://cameraangle.co.uk/doku.php?id=encoding_live_entries_in_controller_missing_ip_and_details&rev=1538721954)

Last update:

2023/03/09 22:35

