# **Packager Live Configuration**

Jun 2017

## Introduction

This section assumes that you or someone has completed the Installation & OS Configuration section.

## **Packager Configuration**

First we need to login, Navigate to your device http://serveripaddress:8080 and you will see the following login page:

$\leftrightarrow$ $\rightarrow$ C (i) Not secure   192	2.168.27.100:8080/ui/accounts/login/?next=/ui/home
ERICSSON	■ MEDIAFIRST VIDEO PROCESSING
	Username
	Username
	Password
	Password
	Login

Login using the following:

Username: admin Password: admin

Once logged in you should see the following page:



On a new server, the Services count will be zero. Servers will be 1 (if this is a stand alone system).

1/4

Last update: 2023/03/09	nackager live configuration http://cameraangle.co.uk/doku.php?id=packager_live_configuration&rev=1407807078
22:35	packager_ive_configuration http://cameraangie.co.uk/doku.php:rd=packager_ive_configuration@rev=1437637676

Click the Servers panel.

ERICSSON	Home / Servers	RST VIDEO PROCESSING			admin 🖁	; ¢
쑴 Home						
Services	Search in table					
-	Name 🗢 IP Addre	ss 🌢 Processina Type	Software	Status	А	ctions
Servers	Pkg1 192.168	27.222 Live Packaging , OD Packaging , Cata	alog , Controller mfvp-controller 1.0.8.7 , m	fvp-packaging 8.0.8.41 connected	0	۲
📽 Settings 🧹	Rows per page: 20	¥				

You will see your server listed, what is supports (Live Packaging, OD Packaging etc.) and the software versions.

### **Configure HTTP Headers of the origin server**

#### HTTP Headers define the access rules to the origin server, and the CDN caching policy.

In the example below, we simply authorize any website to access any content on the origin server. This is not a valid production configuration; however this is fine for testing.

Minimum pattern is \* Access-Control-Allow-Origin:\*

On the left hand menu, click 'Settings'

← → C 🗋 192.168.27.2	22:8080/ui/home			
ERICSSON	■ MEDI	AFIRST VIDEO F	PROCESSING	<u>;</u>
倄 Home				
Services		Services 0		Servers 1
🛢 Servers				
😋 Settings 🗸 🗸	Started	Other status	Connected	Connection lost
Credentials				
H HTTP Headers				

#### Now select 'HTTP Headers'

Add a new entry using \* for Url Pattern and Access-Control-Allow-Origin:\* for the HTTP Headers.

#	Url Pattern	HTTP Headers
≡	*	Access-Control-Allow-Origin:*
+ Add		

Click 'Save and Exit'

#### **Catalog configuration**

A catalog is an output definition, so we can create a catalog for HLS, for Dash, for Smooth Streaming and add the catalog's (outputs) to our packaging service configurations.

Click add service and select catalog

ERICSSON	MEDIAFIRST VIDEO PROCESSING Home / Services				
🖀 Home	Add service - Import service				
Services	Catalog				
■ Servers	Live Packaging				
🕫 Settings 🧹	VOD Packaging Output T Catalog				

This will allow the creation of a new Catalog.

Enter a name for the new Catalog.

Catalog					
	Name*	HLS			
Output Name 🗢	Ţ	ype 🗢	Access URL 🗢	Encryption 🗘	Content repl. 🗢
+ Add new output					

Click Save and Continue (the Add New Output button will not work until you click Save and Continue.

The Catalog will need some outputs defined, you can add multiple outputs to a Catalog, so a single Catalog can have HLS, HSS and Dash outputs for example.

Click on the Add new output button.

This will open the page for new outputs.

Home / Services / Output1	VIDEO PROCESSING					admin 🛓	10
Output							
Name*	HLS						
Туре*	HLS			٣			
Publishing							
Access URL*	HLS						
Playlist distribution URL							
Media distribution URL							
Manifests							
Name		Filtering					
index			ø				
+ Ad	d monifect						
	u maniest						
Scrambling							
Scrambling Encryption*	None			Ŧ			
Scrambling Encryption* Content Replacement	None			Ÿ			
Scrambling Encryption* Content Replacement Replacement type*	None			Ÿ			
Scrambling Encryption* Content Replacement Replacement type* Advanced parameters	None			Y Y			
Scrambling Encryption* Content Replacement Replacement type* Advanced parameters GOP Per chunk*	None 5			Ψ Ψ			
Scrambling Encryption <sup>4</sup> Content Replacement Replacement type <sup>4</sup> Advanced parameters GOP Per chunk <sup>4</sup> Multiplex mode <sup>4</sup>	None 5 Separate video and audio			<b>v</b>			

Enter the following:

```
Name: HLS
Type: HLS (from dropdown list)
Access URL: HLS (this will form part of the URL to retrieve the packaged segments)
```

Click Save and Exit.

From: http://cameraangle.co.uk/ - WalkerWiki - wiki.alanwalker.uk

Permanent link: http://cameraangle.co.uk/doku.php?id=packager\_live\_configuration&rev=1497897078

Last update: 2023/03/09 22:35

