

Regional Stat Mux

Oct 2017

Introduction


Regional Stat Mux is a mechanism where regional services are in a Stat Mux pool with national services, but all the regional services use the same instantaneous bit rate, so any of the regional services can be picked up, and will fit perfectly in to the Mux for that region, as they are all the same bit rate.

This means that switching in and out of regional content no longer requires that service, or the entire Mux, to switch to a CBR operation.

In this example, I am using MFEL v7x, as Regional Stat Mux is not yet available in v8/v10. For the multiplexing I am using MFSP, this is V8. This means that the MFEL is doing the Stat Mux, and the MFSP is just creating our MPTS from the SPTS streams coming from the MFEL. When all products are v8/v10 then the MFSP will do the Stat Mux control of the MFEL.

MFEL Configuration

Below is an image of an MFEL Configuration for Regional Stat Mux. We can see that there are three National Services and two Regional Services.



Looking at National 1 DTT (ignore the others, MGW and OTT, they are CBR) we can see that the **Stat Mux Properties** (in the red box) are:

Group Name: Teracom (the name is not important, this is the name of our Stat Mux group)
Regional ID: None

This is how the Stat Mux Properties of National 1, National 2 and National 3 are configured.

When we look at the Stat Mux Properties for a Regional Service, Regional 1 in this example:

MediaFirst Video Processing

Encoding Live

System

CPU Mem

Distributed Encoding

Statmux

pool1 - 20000 kbps

Teracom - 20000 kbps

National 1

DTT - DVB Extreme - Statmux - 1357 - 6490 kbps13:25:32 - 6549 kbps

MGW - Internet TV DVB - CBR - 8385 kbps1 day 11:58:31 - 8404 kbps

OTT - Internet TV DVB - CBR - 8413 kbps1 day 11:58:30 - 8468 kbps

National 2

DTT - DVB Extreme - Statmux - 1357 - 6490 kbps13:25:26 - 6549 kbps

MGW - Internet TV DVB - CBR - 8391 kbps1 day 11:58:29 - 8410 kbps

National 3

DTT - DVB Extreme - Statmux - 1357 - 6490 kbps13:25:24 - 6549 kbps

MGW - Internet TV DVB - CBR - 8325 kbps1 day 11:58:31 - 8341 kbps

Regional 1

DTT - DVB Extreme - Statmux - 1357 - 6490 kbps03:48:21 - 6549 kbps

Regional 2

DTT - DVB Extreme - Statmux - 1357 - 6490 kbps03:48:07 - 6549 kbps

New Service

DTT

Delete | Duplicate

Name: DTT

Export type: DVB Extreme

Bit rate

Rate control: Statmux

Overall min bit rate: 1357 kbps

Overall max bit rate: 6490 kbps

Overall constant bit rate: 3410 kbps

SCTE 35 reference stream: None

Current mode: VBR

Statmux

Network interface: enp4s0f0 (10.43.3.67)

Group name: Teracom

Regional ID: Sub Group 1

Video quality monitoring

Open the video quality monitor.

Image overlay

Content blackout | Alternate content | Logo insertion | Automation

Image URL:

Image status: No image

Automated

Trigger: None

Manual

Mute audio:

For a Regional Service, we can see that the Stat Mux Properties (in the red box) are:

Group Name: Teracom

Regional ID: Sub Group 1

Both of our Regional Services are in Sub Group 1 in this example, so they will both get the same number of bits, at the same instance in time, even though the content on these services is different.

Remember: This is a version 7 MFEL, and the MFEL is doing the Stat Mux, in Next Gen versions, the MFSP will do the Stat Mux, so this configuration will be done via Controller.

MFSP Configuration

In this example, the MFSP is really just doing remux to create MPTS streams from the SPTS streams coming in from the MFEL.

We have five services coming from our MFEL, National 1, National 2, National 3, Regional 1 and Regional 2. What we will create is two TS outputs, where the TS will contain:

TS1	TS2
National 1	National 1
National 2	National 2
National 3	National 3
Regional 1	Regional 2

Below is part of the configuration for the TS1 of the MFSP.

ERICSSON

Home

Services

Servers

Templates

Failover

MEDIAFIRST VIDEO PROCESSING

Home / Services / Teracom_TS1 / Edit Mux

Mux

Name: Teracom_TS1

Total Bit Rate: 24,000,000 bps

PSI Bit Rate: 150,000 bps

Null Bit Rate: 0 bps

Statistical Bit Rate Allocation: ☐

Output

Primary

Secondary

Stream address: 239.2.40.20

Port: 1234

Network Interface: eno33559296

IP TTL:

Enable RTP: ☐

Server filter: *

Inputs

Name	IP address	Port	Source IP(s)	Actions
National_1	239.0.67.1	1234		<input type="checkbox"/> <input type="checkbox"/>
National_2	239.0.67.2	1234		<input type="checkbox"/> <input type="checkbox"/>
National_3	239.0.67.3	1234		<input type="checkbox"/> <input type="checkbox"/>
Regional_1	239.0.67.4	1234		<input type="checkbox"/> <input type="checkbox"/>

+ Add input

Cancel

Save and Continue

Save and Exit

Copyright © Ericsson 1994-2017. All rights reserved.

Here we can see the four services, National 1, National 2, National 3 and Regional 1. The Second TS output is identical except Regional 1 is replaced with Regional 2.

Overview

The MFEL is encoding 3 National Services and 1 Regional Service using a defined Stat Mux Pool size (20Mbps a second in our case). However, each Regional Service gets the same bits. So we are encoding Regional 1 and Regional 2 using the same bit rate. See below for an example of the Stat Mux bit rates.

Group name: Teracom

Network interface: enp4s0f0 (10.43.3.67)

Total bit rate: 20000 kbps

State:

Edit

Delete

Service	Profile	Description	Video (kbps)	Audio (kbps)	Private (kbps)	Total (kbps)
National 1	DTT	H.264 - 1118 - 6253 kbps - 1280x720	4776	246	0	5022
National 2	DTT	H.264 - 1118 - 6253 kbps - 1280x720	5118	246	0	5364
National 3	DTT	H.264 - 1118 - 6253 kbps - 1280x720	5885	246	0	6131
Regional 1	DTT	H.264 - 1118 - 6253 kbps - 1280x720	3232	246	0	3478
Regional 2	DTT	H.264 - 1118 - 6253 kbps - 1280x720	3232	246	0	3478
			22243	1230	0	23473

Here we can see that the Stat Mux pool (at the top of the image) is 20000 kbps and that Regional 1 and Regional 2 (in the red box) are both the same bit rate (at this instance in time).

We can also observe that although the Stat Mux Pool is 20000 kbps, the Total is listed as 24373 kbps, this is because Region 1 and Region 2 are both using the same bit rate, however, if you do the maths from this image:

National 1	-	5022	National 1	-	5022
National 2	-	5364	National 2	-	5364
National 3	-	6131	National 3	-	6131
Regional 1	-	3478	Regional 2	-	3478
Total	-	19995	Total	-	19995

So when remixed through the MFSP (or any mux) neither TS will go over the 20000 kbps pool size that was allocated.

See it in Action

Here we can see some short videos where you can see this in action.
MFEL Stat Mux.

[960x540|autoplay,loop](#)
[1440x850|autoplay,loop](#)

end

From:

<http://cameraangle.co.uk/> - WalkerWiki - wiki.alanwalker.uk

Permanent link:

http://cameraangle.co.uk/doku.php?id=wiki:regional_stat_mux&rev=1508359688

Last update:

2023/03/09 22:35

